2025/12/01 15:38 1/5 TMSS10MoveScratch

TMSS10MoveScratch

Synopsis

TMSS10MoveScratch [-C scratch capacity] [-R target repository] [-S logon string] [-V volume filter] [-a skip move] [-b skip scratch] [-c config file] [-m scratch maximum]

Description

Resets the scratch flag of each Volume and move scratch Volumes to another Repository.

TMSS10MoveScratch is used to manage Scratch Volumes, it performs 3 functions: 1. Moves all Volumes with a Scratch Flag to the Repository specified in the -R argument. 2. Sets the Scratch Flag for all Volumes. 3. Lists all Volumes with a Scratch Flag.

This command is particularly helpful for platforms such as Tivoli Storage Manager® which deletes scratch tapes from its Volume Table, as you can schedule the command to run once per week to reset all Volumes to Scratch then remove the Scratch Flag using TMSS10Sync during the week. Then when the program is run subsequently the next week, it will move each Volume that still has the Scratch Flag set to a new Repository.



Please note that when running TMSS10MoveScratch with the -R argument set you must be sure that the process that sets the Scratch Flag to false has run. In the event that this is multiple processes (where you have multiple backup catalogs) you must be sure that all processes would have run. In the event that not all Scratch Flags that should have been removed have not been removed it is possible that non-Scratch tapes will be moved.

Options

- C Scratch capacity of Target repository (default = 1000)
- -R Target repository where scratch volumes will be moved to.
- -S The logon string argument sets the Server logon information
- - V Volume Filter which can be used to filter the traversal of Customer, Media, Volume, repository and flag values.
- -a Skip move step (default = false)
- b Skip scratch step (default = false)
- c The config file argument specifies the path to the Batch Configuration File. The Batch
 Configuration File allows you to perform advanced traversal of Customer, Media and Volumes,
 perform advanced barcode pre and post processing and route program output to syslogd.
 Configuration File capabilities vary from program to program but the syntax remains the same.
 In the event that logic is not supported it will simply be ignored.

Last update: 2025/01/21 22:07

• -m Scratch maximum (default = 1000000)

Technical Support

The TapeTrack Software is commercially supported by a full time help desk staff. If you are experiencing problems or want some advice on how to configure or use the product please see the Accessing Technical Support page.

Exit Statuses

- 1. **zero** Program has ended successfully.
- 2. **non-zero** Program has not ended successfully.

Environment

TMSSSERVERPROXY If defined the program will route all TapeTrack TCP/IP traffic through a HTTPS proxy. The value of the variable should be in the format user:password@host:port. To debug the proxy connection use variable **TMSSAPILOGDIR**.

TMSSAPILOGDIR If defined the program will write out a trace file to this directory.

TMSSPWPATH When no password value is passed in the logon string the program will look for the password in file \etc\tapetrack\user, where user is the user value passed in the logonstring. If you wish to change this default path, you can set the path in TMSSPWPATH.

Files

stdout: Output Reports.

stderr: Diagnostic messages.

stdin: Program input.

Example

Move maximum of 1 scratch volume to repository LIBR for customer US04, media LTO and set scratch flag for rest of volumes.

Command line syntax

TMSS10MoveScratch -S doco:-doco@localhost -C 1 -R LIBR -V "US04.LT0.*"

https://rtfm.tapetrack.com/ Printed on 2025/12/01 15:38

2025/12/01 15:38 3/5 TMSS10MoveScratch

Output

System: TapeTrac Report Description: Scratch Production Time: Monday, Time) Report Width: 165 byte	List May 21, 2018 - 11:13	:58 (AUS Eastern Stan	dard
Seq. Barcode Message	Current Target	New Target	Age
1 US04.LT0.000011L5 M31:14	Scratch Volumes	Library	

Produce scratch report only for Customer US04, media LTO.

Command line syntax

```
TMSS10MoveScratch -S doco:-doco@localhost -b -V "US04.LT0.*"
```

Output

System: TapeTrac	ck					
Report Description: Scratch List						
Production Time: Monday,	May 21, 2018 - 11:30	:11 (AUS Eastern Standard				
Time)						
Report Width: 165 bytes						
Con Domondo	Cumment Tanget	No To much				
Seq. Barcode	Current Target	New Target Age				
Message						
1 11004 1 TO 0000011 2	Caratah Valumas	NI / A				
1 US04.LT0.000001L3	Scratch Volumes	N/A				
M55:19	Caratal Walana	N1 / A				
2 US04.LT0.000001L5	Scratch Volumes	N/A				

M55:19				
3 US04.L	_T0.000002L5	Scratch	Volumes	N/A
	_T0.000003L5	Scratch	Volumes	N/A
M55:19 5 US04.L	_T0.000004L5	Scratch	Volumes	N/A
M55:19 6 US04.L	_T0.000004L6	Scratch	Volumes	N/A
M55:19	_T0.000005L5	Scratch	Volumes	N/A
M55:19				
M55:19	_T0.000005L6			N/A
9 US04.L M55:19	_T0.000006L5	Scratch	Volumes	N/A
10 US04.L M55:19	_T0.000006L6	Scratch	Volumes	N/A
	_T0.000007L5	Scratch	Volumes	N/A
12 US04.L	_T0.000007L6	Scratch	Volumes	N/A
M55:19 13 US04.L	_T0.000008L5	Scratch	Volumes	N/A
M55:19 14 US04.L	_T0.000008L6	Scratch	Volumes	N/A
M55:18	_T0.000009L5	Scratch	Volumes	N/A
M47:27				
M47:27	_T0.000009L6			N/A
17 US04.L M47:27	_T0.000010L5	Scratch	Volumes	N/A
18 US04.L M47:27	_T0.000010L6	Scratch	Volumes	N/A
	_T0.000011L5	Library		N/A
20 US04.L	_T0.000012L5	Scratch	Volumes	N/A
M47:27 21 US04.L	_T0.000013L5	Scratch	Volumes	N/A
M47:27 22 US04.L	_T0.000014L5	Library		N/A
M46:03	_T0.000015L5	Library		N/A
M46:03		_		
M46:03	_T0.000016L5	Library		N/A
25 US04.L M46:03	_T0.123	Library		N/A

https://rtfm.tapetrack.com/ Printed on 2025/12/01 15:38

From:

https://rtfm.tapetrack.com/ - TapeTrack Documentation

Permanent link:

https://rtfm.tapetrack.com/cli/tmss10movescratch?rev=1526866320

Last update: 2025/01/21 22:07

