

setwritetimeformat

## SetWriteTimeFormat

Define the way that the WRITETIME field should be converted into a time value.

### Phase

This instruction is used by the TapeTrack Synchronization Engine.

### Syntax

**SetWriteTimeFormat**(*format*);

*string format;*

**format** The Write Time format in strftime(3) format.



It should be noted that by the time this function is run the INI engine has already tried to resolve environmental variables so it is necessary to include two percentage symbols for each symbol that would usually be required by strftime(3).

### Example

**SetWriteTimeFormat: Extract the Write Time in format HH:MM:SS YYYY-MM-DD.**

Extract(WRITETIME, 10, 20, 0);	Extract WRITETIME from field 10, length 20.
SetWriteTimeFormat("H:M:S Y-%m-%d");	Set the Write Time in format HH:MM:SS YYYY-MM-DD.

From:

<https://rtfm.tapetrack.com/> - TapeTrack Documentation

Permanent link:

<https://rtfm.tapetrack.com/engine sync/setwritetimeformat?rev=1534278106>

Last update: **2025/01/21 22:07**

