

Adding A New User

Prerequisites

- Active User-ID with tapemaster rights
- TapeMaster access



If assigning tapemaster rights to the new User you must login as the tapemaster User-ID

Creating New User-ID

In TapeMaster open the Group/User Administration window via the main menu Administration → Group/User Administration.

Right-click in the white space on the User Administration screen and select Add.

Identity

Add New User

Identity IP Ranges Access

Identity

ID

Name

Group

ID

Options

Administrative rights False

Scan-In Only False

Disabled False

No Scanner False

No Time-Out False

tapemaster rights False

Allow access inheritance False

Certify False

AD Domain

Require AD Group False

Client Access

TapeMaster True

Lite True

Checkpoint False

Sync True

Details

Email Address

Description

Defaults

Customer-ID <No Selection>

One-Time Password

Enable **True**

Activated False

Certify

User can create new Certificates

Save Cancel Help

Set the users identity fields



If using windows Active Domain to log into TapeTrack, the username must match your AD username

The Identity tab provides fields to update the:

- **Identity**
 - **User-ID:** The User-ID will be the user name that the user uses to login to TapeTrack products.
 - **Name:** The name is the User's desired display name.
- **Group**
 - **Group-ID:** Select group to assign user to from the drop-down list or [add new group](#).
 - **Role:** Hierarchical role of the User.

• Options

- **Administrative rights:** When set to True the User will have Administration Rights with Server Administrator privileges or the ability to Add/Delete Customers and Media Types.
- **Scan-In Only:** When set to True the User will only be able to Scan tapes into the system.
- **Disabled:** When set to True the User's access will be in a disabled status, so that they are not able to access any TapeTrack products. This does not delete the User.
- **No Scanner:** When set to True the Barcode Scanning Window will provide an auto-complete drop-down.
- **No Time-Out:** By default, all User's are logged out of TapeMaster after ten minutes of inactivity. Setting this to True, the selected User will not time out.
- **tapemaster rights:** When set to True, it allows the User to gain the same administrative rights as the tapemaster superuser account. Only the User-ID tapemaster can add tapemaster rights to another user.
- **Allow access inheritance:** Allows User to inherit another User's access rights using variable `TMSUSERINHERIT` with [Command Line Utility](#) Programs
- **Certify:** Assigns the ability to [generate certificates](#).
- **AD Domain:** This is required if the User logs on to TapeTrack with their Active Directory Username and Password.
- **Require AD Group:** When set to True, the User must use their [Active Directory](#) credentials to logon.

• Client Access

- **TapeMaster:** Authorizes User-ID access to TapeMaster
- **Lite:** Authorizes User-ID access to Lite
- **Checkpoint:** Authorizes User-ID access to Checkpoint
- **Sync:** Authorizes User-ID access to Sync software.

• Details

- **Email Address:** Allows inclusion of user email, which may be used instead of username to log into TapeTrack directly (ie not using Active Directory)
- **Description:** Add description to User-ID.

• Defaults

- **Customer-ID:** Sets Customer-ID for User in Scan-In window. Once Customer-ID is set, Media-ID field will be displayed.
- **Media-ID:** Sets Media-ID for User in Scan-In window.

• One-Time-Password

- **Enabled:** Enables the use of 2FA or One time password for login.
- **Activated:** Shows if 2FA or One time password is activated. Activated only displays if Enabled is set to True.




If using windows Active Domain to log into TapeTrack, the username must match your AD username

IP Ranges

The IP Ranges tab sets restrictions on which IP addresses a User can access the TapeTrack Server from.

If setting IP's, ensure Users have a static IP address so they are not denied access if trying to access

from a dynamic address such as using a remote or home connection.



Seq.	IP	Mask
1	0.0.0.0	

To add or delete, right-click the window and select from the menu.

Global Access (0.0.0.0) will allow access from any IP, this value will need to be removed if added a restricted IP list as all values in the list are valid.

Access

The Access tab sets permissions for which Customers the selected User can access and how that User can interact with Volumes in the selected Customer.

Add New User

Identity IP Ranges Access

Customer-ID	Access
Read	False
Write	False
Alter	False
Catalog	False

Add

Customer-ID	Access
There are no items to display in this list.	

Access Prediction

Customer	Description	Access
There are no items to display in this list.		

Total Items 0

Save Cancel Help

- **Customer-ID:** Enter the Customer-ID for the Customer that the User should have access to.
 - US01 will give access to US01 only
 - US* will give access to all customers starting with US
 - * will give access to all customers
- **Read:** Allows the User to view but not update Volumes in the above Customer. Must be enabled for the User to be able to view Volumes in the selected Customer-ID.
- **Write:** Allows the User to perform basic operations for Volumes to the selected Customer.
- **Alter:** Allows the User to Add and Delete Media and Volumes to the selected Customer.
- **Catalog:** Allows User to access Catalog information on the selected Customer.

For each Customer access, click Add to commit the data. Predicted access rights will then be displayed in the lower window.

Once all data has been entered, click Save to create User.

The randomly generated password for the new user will be displayed in the Random password Set

window. This window has three options: * Click the Copy password button to copy generated password to your clipboard.

- Clicking the Copy message button will give you the text “ A new TapeTrack User-ID has been created for you to use. You can access this account using the User-ID (Current User) and the password(B@7NpJ%7GR)” copied to your clipboard for convenience when sending a message to the user with login details.
- Clicking the Email message button will open up your default email client with the same text as Copy message.

Use one of these options to notify the new user of their login details.

If you want to manually set a password, or are using Active Directory credentials, you can close the Random password Set window without needing to record the random password.

If you are manually setting the password, from the main menu select Administration → Group/User Administration.

TapeTrack TapeMaster™ (GazillaByte)

File Administration Favorites Tools View Help

Customer Filter

GazillaByte - Production

- US00 - United State
 - US01 - New York
 - US02 - Los Angel
 - CONT - Conta
 - LTO - LTO Car
 - US03 - North Car

Volumes Los Angeles Data Center LTO Cartridge

ID	Current Location	Target Location	Next Move	Description
Enter text ...	Enter text here	Enter text here	Enter tex...	Enter text here
000000L6	Offsite Vault	Library	Permanent	
000001L6	Library	Offsite Vault	Permanent	
000002L6	Library	Offsite Vault	Permanent	
000003L6	Library		Permanent	
000004L6	Library		Permanent	
000005L6	Library	Offsite Vault	Permanent	
000006L6	Library	Offsite Vault	Permanent	
000007L6	Library	Offsite Vault	Permanent	
000008L6	Library		Permanent	
000009L6	Library		Permanent	
000010L6	Library		Permanent	
000011L6	Offsite Vault		Permanent	
000012L6	Library		Permanent	
000013L6	Library		Permanent	
000014L6	Library		Permanent	
000015L6	Library		Permanent	
000016L6	Offsite Vault	Library	Permanent	
000017L6	Offsite Vault	Library	Permanent	

Total Items 1,585

Repositories


Gemtrac Library Transport Offsite Vault

Connection 127.0.0.1 uses AES 256 bit encryption

Right click on the required User-ID and select from the popup menu, Management → Reset Password to open the **Password Change** window.




If you don't see the Management menu when right clicking on a User-ID, please see [Previous releases method](#) for resetting passwords



In the Password Change window to set a known password value, insert new password in the New Password field.

Type password in the Password (again) field to confirm the password value and click OK to commit the updated password.

A screenshot of a 'Password Change' dialog box. The title bar says 'Password Change' with a close button. Inside, there's a large yellow padlock icon. Below it, there are three input fields: 'User' (containing 'jdoe'), 'New Password', and 'Password (again)'. A 'Random' button is below the password fields. At the bottom are 'OK' and 'Cancel' buttons. A mouse cursor is pointing at the 'User' field.

Password Change

User

New Password

Password (again)

It is best practice to have any user you change the password for to have them change their password the next time they logon to ensure user-ID security.

See Also

[Troubleshooting: Add user errors](#)
[Change Password](#)

[technote](#), [user](#), [tapemaster](#), [lite](#), [password](#)

From:
<https://rtfm.tapetrack.com/> - **TapeTrack Documentation**

Permanent link:
https://rtfm.tapetrack.com/technote/add_user?rev=1784080398

Last update: **2026/07/15 01:53**

