2025/10/17 17:53 1/1 SetWriteTimeFormat

## **SetWriteTimeFormat**

Define the way that the WRITETIME field should be converted into a time value.

## **Phase**

This instruction is used by the TapeTrack Synchronization Engine.

## **Syntax**

SetWriteTimeFormat(format);

string format;

format The Write Time format in strptime(3) format. Min Length: 1 Max Length 32



It should be noted that by the time this function is run the INI engine has already tried to resolve environmental variables so it is necessary to include two percentage symbols for each symbol that would usually be required by strptime(3).

## **Example**

Extract the Write Time in format HH:MM:SS YYYY-MM-DD.

```
Extract(WRITETIME, 10, 20, 0);
SetWriteTimeFormat("%%H:%%M:%%S %%Y-%m-%d");
```

import engine, sync engine

From:

https://rtfm.tapetrack.com/ - TapeTrack Documentation

Permanent link:

https://rtfm.tapetrack.com/engine/sync/setwritetimeformat?rev=158328226

Last update: 2025/01/21 22:07

