
Pattern matching

TapeTrack has powerful pattern matching functionality that can be utilized globally in TapeMaster.

String Pattern Matching

To illustrate the effects of where and how the asterisk wildcard affects search results all examples will be performed against the following volume values.

100000L4, 100001L4, 100002L4, 100003L4, 100004L4, 100012L4, 100022L4, 200000L5, 200012L5, 200022L5



Asterisk (*)

The **Asterisk is used** as a wildcard to allow string matching in multiple positions and variable string lengths. image

- An Asterisk before a set of characters will show all items that end with those characters.
- An **Asterisk** after a set of characters will show all items that begin with those characters.
- If used on its own, the **Asterisk** will display all data in that column.
- Using two **Asterisks**, one on either side of a character or set of characters will show all items containing that character or set of characters at any character position.

The Asterisk does not need to be used when entering a full Object-ID or when searching for Flags in the Volume List.

Last update: 2025/01/21 22:07

Question Mark (?)

The **Question Mark** is used to indicate that any character can exist in a specific character position. image

Square Brackets ([])

Square Brackets can be used to provide parameters for a specific character position that are longer than one character. There are four different configurations:

Multiple Characters

When multiple characters are put in a **Square Bracket**, any of the characters listed will be displayed at the specified character position. image

Vertical Bar (|)

When two or more characters are placed between **Square Brackets** and separated by **Vertical Bars**, the **Vertical Bar** will act as the word "OR" displaying any of the characters. image

Hyphen (-)

When two characters are placed between **Square Brackets** and separated by a **Hyphen**, any character alphanumerically between the two characters will display. image

Exclamation Point (!)

When the **Exclamation Point** is placed immediately following the left **Square Bracket** in a set of **Square Brackets**, any character except for the characters listed after the **Exclamation Point** will display. This functionality also works with **Multiple Characters**, **Vertical Bars**, and **Hyphens**. image

Date Pattern Matching

TapeTrack Date Format

TapeTrack allows you to represent dates both as literal date values and date calculations.

Syntax

• YYYY-MM-DD: ISO Date format

*: Today

https://rtfm.tapetrack.com/ Printed on 2025/04/18 13:26

- *[+-]x: Today + or x days
- M: The first day of this month
- m: The last day of this month
- Y: The first day of the year
- y: The last day of the year
- M+-x: The first day of the month + or x months
- M+-x+-y: The first day of the month + or x months + or y days
- Y+-x: The first day of the year + or x months
- Y+-x+-y: The first day of the year + or x years + or y months
- Y+-x+-y+-z: The first day of the year + or x years + or y months + or x days

Examples

*-10	10 days ago
Υ	the beginning of this year
M-0-	the last day of last month
y-1	the last day of last year
Y-1+3-1	the last day of February last year

From:

https://rtfm.tapetrack.com/ - TapeTrack Documentation

Permanent link:

https://rtfm.tapetrack.com/general/pattern_matching?rev=1506303856

Last update: **2025/01/21 22:07**

